

# Product data sheet

## AU Rotary LED dimmer 400W



### Reference number

AU-RLD400W

Rotary dimmer insert 60-400 W

### Intended use

- Switching and dimming incandescent lamps, HV halogen lamps and TRONIC transformers with halogen lamps
- Suitable for mixed operation up to the specified output
- Installation in appliance box according to CLIPSAL Standard panel





### Product characteristics

- Dimming method: Leading edge phase control

### Technical data

Rated voltage:	AC 220-240 V ~ , 50Hz
Connected load:	60 - 400W
Dimming method:	Leading edge phase control
Type of loads:	220 - 240V AC Incandescent lamps High voltage halogen lamps Dimmable electrical transformer and iron transformer
Connection:	screw terminals

### Rating Label

<b>SHYUSC</b>	SUITABLE FOR:				
AU-RLD400W	 INCANDESCENT LIGHTING  240V HALOGEN LAMPS  LOW VOLTAGE HALOGEN LAMPS  LIGHTING WITH ELECTRONIC TRANSFORMERS 220-240V~50Hz				
ROTARY CONTROLLED LEADING DIMMER					
<b>400W</b> $\epsilon$	<table border="1"> <tr> <td>Min LAMP LOAD</td> <td>60W</td> </tr> <tr> <td>Max LAMP LOAD</td> <td>400W</td> </tr> </table>	Min LAMP LOAD	60W	Max LAMP LOAD	400W
Min LAMP LOAD	60W				
Max LAMP LOAD	400W				