

Product data sheet

AU Push button LED dimmer 350VA

Reference number

AU-PBD350VA

Push button dimmer insert 10 - 350 VA

Intended use

- Dimmable LED
- Switching and dimming incandescent lamps, HV halogen lamps and TRONIC transformers with halogen lamps
- Suitable for mixed operation up to the specified output
- Installation in appliance box according to CLIPSAL and HPM Standard panel

Product characteristics

- Dimming method: trailing edge phase control
- Electronic short-circuit protection
- Overload protection
- Over current protection
- Over temperature protection

Technical data

Rated voltage:	AC 220-240 V ~ , 50Hz
Connected load:	10VA - 350VA(1 - 15 LEDs, 150W max.)
Dimming method:	Trailing edge phase control
Type of loads:	Dimmable LED 220 - 240V AC Incandescent lamps High voltage halogen lamps Dimmable electrical transformer and iron transformer Mixed load of the specified types
Connection:	screw terminals
Approvals:	RCM SAA162773

Rating Label

	SHYUSC AU-PBD350VA PUSH BUTTON CONTROLLED LED TRAILING DIMMER 350VA	SUITABLE FOR:  DIMMABLE LED LIGHTING  INCANDESCENT LIGHTING 240V HALOGEN LAMPS  LOW VOLTAGE HALOGEN LIGHTING WITH ELECTRONIC TRANSFORMERS 220-240V~50Hz <table border="1"> <tr> <td>MIN LAMP LOAD</td> <td>10VA</td> </tr> <tr> <td>MAX LAMP LOAD</td> <td>350VA</td> </tr> </table>	MIN LAMP LOAD	10VA	MAX LAMP LOAD	350VA
	MIN LAMP LOAD	10VA				
MAX LAMP LOAD	350VA					
						