



Product data sheet

Dimmer with 2 - way push switch



Reference number

UK-PRLD400W

Push dimmer insert 60 - 400 W

with 2-way push switch

Intended use

- Switching and dimming incandescent lamps, HV halogen lamps and TRONIC transformers with halogen lamps
- Suitable for mixed operation up to the specified output
- Installation in appliance box according to BS Standard panel

Product characteristics

- Dimming method: leading edge phase control

Rating Label

Load L1 L2


SHYUSC


UK-PRLD400VA

DE-RATING MAY BE REQUIRED

220-240V ~, 50Hz E

LEADING EDGE

 =60-400W

 =60-400W



Technical data

Rated voltage:

AC 220-240 V ~, 50 Hz

Connected load:

60VA - 400VA

Dimming method:

Leading edge phase control

Type of loads:

220 - 240V AC Incandescent lamps

High voltage halogen lamps

Dimmable electrical transformer and iron transformer

Connection:

screw terminals